

## REVO IPA-140

### PRODUCT DESCRIPTION

The Norma Revo IPA-140 integrated amplifier represents a definitive choice for amplification. Its high power (140W/80hm) and the ability to drive the most demanding speakers, make it an extremely versatile amp.

Versatility is enhanced by the ability to customize the input / output connections and to insert the Phono MM / MC board. The elegant and sophisticated style is perfectly in tune with its sound personality.

Power, dynamics, speed and transparency are combined to create outstanding musicality and a total absence of listening fatigue. The inside workings show that the technical refinement follows the same philosophy. The Revo IPA-140 uses a proprietary circuitry, regulated high-speed power, low noise and is built with a careful selection of the best materials available.

*Disclaimer: Norma Audio reserves the right to change specification without notice.*



### GALLERY IMAGES



## PRODUCT SPECIFICATIONS

<b>Brand</b>	Norma Audio
<b>Inputs</b>	4 RCA, 1 XLR Balanced, optional Phono, 1 USB DAC optional
<b>Input impedance</b>	47Kohm (not selected input) / 10 Kohm (selected input)
<b>Input Configuration</b>	Phono MM/MC, Line, Direct AV, Balanced
<b>Output Signal</b>	Passive Pre Out , Active Pre Out, Tape out, Subwoofer out
<b>Output Impedance (Pre-Out)</b>	200 ohm
<b>Output Power</b>	1 Binding Post pairs, accept 4mm banana plugs and fork
<b>Frequency Response</b>	0 Hz – 1.8 MHz (-3dB, non filtered)
<b>Output Power</b>	140 W RMS / 8 Ohm – 280 W RMS / 4 Ohm (each channel)
<b>Gain</b>	34 dB
<b>Configuration</b>	Dual Mono
<b>Circulation</b>	Solid state
<b>Power devices</b>	MosFet, 3 pairs for each channel
<b>Output current available</b>	36 A continuous, 150 A peak (per channel)
<b>Ability to filter</b>	72.000 uF, 12 electrical capacitor for each channel
<b>Electric transformers</b>	2 toroidal special audio use, 400 VA per channel
<b>Supply</b>	230 V AC / 50 Hz, (100V AC or 115 VAC / 50-60Hz in some country)
<b>Dimensions (HxWxD)</b>	110 x 430 x 365 mm, (excluding feet, knob and rear jacks)
<b>Weight</b>	25 Kg
<b>Note</b>	Stereo Integrated Amplifier fully remote controlled